

3 Pin Surface Mount Zener Diodes

Search:

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
MMBZ5221B	18A	2.28	2.4	2.52	20	225	SOT-23	datasheet
MMBZ5222B	18B	2.37	2.5	2.63	20	225	SOT-23	datasheet
MMBZ5223B	18C	2.56	2.7	2.84	20	225	SOT-23	datasheet
MMBZ5224B	18D	2.66	2.8	2.94	20	225	SOT-23	datasheet
MMBZ5225B	18E	2.85	3	3.15	20	225	SOT-23	datasheet
MMBZ5226B	8A	3.13	3.3	3.47	20	225	SOT-23	datasheet
MMBZ5227B	8B	3.42	3.6	3.78	20	225	SOT-23	datasheet
MMBZ5228B	8C	3.7	3.9	4.1	20	225	SOT-23	datasheet
MMBZ5229B	8D	4.08	4.3	4.52	20	225	SOT-23	datasheet
MMBZ5230B	8E	4.46	4.7	4.94	20	225	SOT-23	datasheet
MMBZ5231B	8F	4.84	5.1	5.36	20	225	SOT-23	datasheet
MMBZ5232B	8G	5.32	5.6	5.88	20	225	SOT-23	datasheet
MMBZ5233B	8H	5.7	6	6.3	20	225	SOT-23	datasheet
MMBZ52	8J	5.8	6.2	6.5	20	225	SOT-	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
34B		9		1			23	eet
MMBZ5235B	8K	6.46	6.8	7.14	20	225	SOT-23	datasheet
MMBZ5236B	8L	7.12	7.5	7.88	20	225	SOT-23	datasheet
MMBZ5237B	8M	7.79	8.2	8.61	20	225	SOT-23	datasheet
MMBZ5238B	8N	8.26	8.7	9.14	20	225	SOT-23	datasheet
MMBZ5239B	8P	8.64	9.1	9.56	20	225	SOT-23	datasheet
MMBZ5240B	8Q	9.5	10	10.5	20	225	SOT-23	datasheet
MMBZ5241B	8R	10.4	11	11.55	20	225	SOT-23	datasheet
MMBZ5242B	8S	11.4	12	12.6	20	225	SOT-23	datasheet
MMBZ5243B	8T	12.35	13	13.65	9.5	225	SOT-23	datasheet
MMBZ5244B	8U	13.3	14	14.7	9	225	SOT-23	datasheet
MMBZ5245B	8V	14.25	15	15.75	8.5	225	SOT-23	datasheet
MMBZ5246B	8W	15.2	16	16.8	7.8	225	SOT-23	datasheet
MMBZ5247B	8X	16.15	17	17.85	7.4	225	SOT-23	datasheet
MMBZ5248B	8Y	17.1	18	18.9	7	225	SOT-23	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
MMBZ5249B	8Z	18.05	19	19.95	6.6	225	SOT-23	datasheet
MMBZ5250B	81A	19	20	21	6.2	225	SOT-23	datasheet
MMBZ5251B	81B	20.9	22	23.1	5.6	225	SOT-23	datasheet
MMBZ5252B	81C	22.8	24	25.2	5.2	225	SOT-23	datasheet
MMBZ5253B	81D	23.75	25	26.25	5	225	SOT-23	datasheet
MMBZ5254B	81E	25.65	27	28.35	4.6	225	SOT-23	datasheet
MMBZ5255B	81F	26.6	28	29.4	4.5	225	SOT-23	datasheet
MMBZ5256B	81G	28.5	30	31.5	4.2	225	SOT-23	datasheet
MMBZ5257B	81H	31.35	33	34.65	3.8	225	SOT-23	datasheet
MMBZ5258B	81J	34.2	36	37.8	3.4	225	SOT-23	datasheet
MMBZ5259B	81K	37.05	39	40.95	3.2	225	SOT-23	datasheet
MMBZ5260B	81L	40.85	43	45.15	3	225	SOT-23	datasheet
MMBZ5261B	81M	44.65	47	49.35	2.7	225	SOT-23	datasheet
MMBZ5262B	81N	48.45	51	53.55	2.5	225	SOT-23	datasheet
MMBZ52	81P	53.	56	58.	2.2	225	SOT-	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
63B		2		8			23	eet
MMBZ5264B	81Q	57	60	63	2.1	225	SOT-23	datasheet
MMBZ5265B	81R	58.9	62	65.1	2	225	SOT-23	datasheet
MMBZ5266B	81S	64.6	68	71.4	1.8	225	SOT-23	datasheet
MMBZ5267B	81T	71.25	75	78.75	1.7	225	SOT-23	datasheet
MMBZ5268B	81U	77.9	82	86.1	1.5	225	SOT-23	datasheet
MMBZ5269B	81V	82.65	87	91.35	1.4	225	SOT-23	datasheet
MMBZ5270B	81W	86.45	91	95.55	1.4	225	SOT-23	datasheet
BZX84C2V4	Z11	2.2	2.4	2.6	5	225	SOT-23	datasheet
BZX84C2V7	Z12	2.5	2.7	2.9	5	225	SOT-23	datasheet
BZX84C3V0	Z13	2.8	3	3.2	5	225	SOT-23	datasheet
BZX84C3V3	Z14	3.1	3.3	3.5	5	225	SOT-23	datasheet
BZX84C3V6	Z15	3.4	3.6	3.8	5	225	SOT-23	datasheet
BZX84C3V9	Z16	3.7	3.9	4.1	5	225	SOT-23	datasheet
BZX84C4V3	W9	4	4.3	4.6	5	225	SOT-23	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
BZX84C4V7	Z1	4.4	4.7	5	5	225	SOT-23	datasheet
BZX84C5V1	Z2	4.8	5.1	5.4	5	225	SOT-23	datasheet
BZX84C5V6	Z3	5.2	5.6	6	5	225	SOT-23	datasheet
BZX84C6V2	Z4	5.8	6.2	6.6	5	225	SOT-23	datasheet
BZX84C6V8	Z5	6.4	6.8	7.2	5	225	SOT-23	datasheet
BZX84C7V5	Z6	7	7.5	7.9	5	225	SOT-23	datasheet
BZX84C8V2	Z7	7.7	8.2	8.7	5	225	SOT-23	datasheet
BZX84C9V1	Z8	8.5	9.1	9.6	5	225	SOT-23	datasheet
BZX84C10	Z9	9.4	10	10.6	5	225	SOT-23	datasheet
BZX84C11	Y1	10.4	11	11.6	5	225	SOT-23	datasheet
BZX84C12	Y2	11.4	12	12.7	5	225	SOT-23	datasheet
BZX84C13	Y3	12.4	13	14.1	5	225	SOT-23	datasheet
BZX84C15	Y4	13.8	15	15.6	5	225	SOT-23	datasheet
BZX84C16	Y5	15.3	16	17.1	5	225	SOT-23	datasheet
BZX84C1	Y6	16.	18	19.	5	225	SOT-	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
8		8		1			23	eet
BZX84C20	Y7	18.8	20	21.2	5	225	SOT-23	datasheet
BZX84C22	Y8	20.8	22	23.3	5	225	SOT-23	datasheet
BZX84C24	Y9	22.8	24	25.6	5	225	SOT-23	datasheet
BZX84C27	Y10	25.1	27	28.9	2	225	SOT-23	datasheet
BZX84C30	Y11	28	30	32	2	225	SOT-23	datasheet
BZX84C33	Y12	31	33	35	2	225	SOT-23	datasheet
BZX84C36	Y13	34	36	38	2	225	SOT-23	datasheet
BZX84C39	Y14	37	39	41	2	225	SOT-23	datasheet
BZX84C43	Y15	40	43	46	2	225	SOT-23	datasheet
BZX84C47	Y16	44	47	50	2	225	SOT-23	datasheet
BZX84C51	Y17	48	51	54	2	225	SOT-23	datasheet
BZX84C62	Y19	58	62	66	2	225	SOT-23	datasheet
BZX84C75	Y21	70	75	79	2	225	SOT-23	datasheet
BZX84B2V7	32	2.69	-	2.91	5	225	SOT-23	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
BZX84B3V0	42	3.01	-	3.22	5	225	SOT-23	datasheet
BZX84B3V3	52	3.32	-	3.53	5	225	SOT-23	datasheet
BZX84B3V6	62	3.6	-	3.845	5	225	SOT-23	datasheet
BZX84B3V9	72	3.89	-	4.16	5	225	SOT-23	datasheet
BZX84B4V3	82	4.17	-	4.43	5	225	SOT-23	datasheet
BZX84B4V7	92	4.55	-	4.75	5	225	SOT-23	datasheet
BZX84B5V1	A2	4.98	-	5.2	5	225	SOT-23	datasheet
BZX84B5V6	C2	5.49	-	5.73	5	225	SOT-23	datasheet
BZX84B6V2	E2	6.06	-	6.33	5	225	SOT-23	datasheet
BZX84B6V8	F2	6.65	-	6.93	5	225	SOT-23	datasheet
BZX84B7V5	H2	7.28	-	7.6	5	225	SOT-23	datasheet
BZX84B8V2	J2	8.02	-	8.36	5	225	SOT-23	datasheet
BZX84B9V1	L2	8.85	-	9.23	5	225	SOT-23	datasheet
BZX84B100	05	9.77	-	10.21	5	225	SOT-23	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
BZX84B11	15	10.76	-	11.22	5	225	SOT-23	datasheet
BZX84B12	25	11.74	-	12.24	5	225	SOT-23	datasheet
BZX84B13	35	12.91	-	13.49	5	225	SOT-23	datasheet
BZX84B15	45	14.34	-	14.98	5	225	SOT-23	datasheet
BZX84B16	55	15.85	-	16.51	5	225	SOT-23	datasheet
BZX84B18	65	17.56	-	18.35	5	225	SOT-23	datasheet
BZX84B20	75	19.52	-	20.39	5	225	SOT-23	datasheet
BZX84B22	85	21.54	-	22.47	5	225	SOT-23	datasheet
BZX84B24	95	23.72	-	24.78	5	225	SOT-23	datasheet
BZX84B27	A5	26.19	-	27.53	5	225	SOT-23	datasheet
BZX84B	C5	29.1	-	30.6	5	225	SOT-23	datasheet

Device	Device Marki ng	VZ (V) Mi n	VZ (V) No m	VZ (V) Ma x	@ IZT (m A)	PD(m W)	Packa ge	PDF Datash eet
30		9		9			3	et
BZX84B 33	E5	32.1 5	-	33.7 9	5	225	SOT-2 3	datashe et
BZX84B 36	F5	35.0 7	-	36.8 7	5	225	SOT-2 3	datashe et