

2 Pin Surface Mount Zener Diodes

Search:

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
MM9D2V4	J	2.28	-	2.52	5	200	SOD-923	datasheet
MM9D2V7	E**	2.57	-	2.84	5	200	SOD-923	datasheet
MM9D3V0	T**	2.85	-	3.15	5	200	SOD-923	datasheet
MM9D3V3	Q	3.14	-	3.47	5	200	SOD-923	datasheet
MM9D3V6	3**	3.42	-	3.78	5	200	SOD-923	datasheet
MM9D3V9	V**	3.71	-	4.1	5	200	SOD-923	datasheet
MM9D4V3	Y**	4.09	-	4.52	5	200	SOD-923	datasheet
MM9D4V7	3	4.47	-	4.94	5	200	SOD-923	datasheet
MM9D5V1	4	4.85	-	5.36	5	200	SOD-923	datasheet
MM9D5V6	5	5.32	-	5.88	5	200	SOD-923	datasheet
MM9D6V2	6	5.89	-	6.51	5	200	SOD-923	datasheet
MM9D6V8	A*	6.46	-	7.14	5	200	SOD-923	datasheet
MM9D7V5	D*	7.13	-	7.88	5	200	SOD-923	datasheet
MM9D	E*	7.7	-	8.6	5	200	SOD-9	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
8V2		9		1			23	eet
MM9D 9V1	F*	8.65	-	9.56	5	200	SOD-923	datasheet
MM9V 10V	J*	9.5	-	10.5	5	200	SOD-923	datasheet
MM9V 11V	K*	10.45	-	11.55	5	200	SOD-923	datasheet
MM9V 12V	L*	11.4	-	12.6	5	200	SOD-923	datasheet
MM9V 13V	P*	12.35	-	13.65	5	200	SOD-923	datasheet
MM9D 15V	Q*	14.25	-	15.75	5	200	SOD-923	datasheet
MM9D 16V	R*	15.2	-	16.8	5	200	SOD-923	datasheet
MM9D 18V	T*	17.1	-	18.9	5	200	SOD-923	datasheet
MM9D 20V	V*	19	-	21	5	200	SOD-923	datasheet
MM9D 22V	Y*	20.9	-	23.1	5	200	SOD-923	datasheet
MM9D 24V	F	22.8	-	25.2	5	200	SOD-923	datasheet
MM8D 2V4	J	2.28	-	2.52	5	200	SOD-882	datasheet
MM8D 2V7	E**	2.57	-	2.84	5	200	SOD-882	datasheet
MM8D 3V0	T**	2.85	-	3.15	5	200	SOD-882	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
MM8D 3V3	Q	3.14	-	3.47	5	200	SOD-882	datasheet
MM8D 3V6	3**	3.42	-	3.78	5	200	SOD-882	datasheet
MM8D 3V9	V**	3.71	-	4.1	5	200	SOD-882	datasheet
MM8D 4V3	Y**	4.09	-	4.52	5	200	SOD-882	datasheet
MM8D 4V7	7	4.47	-	4.94	5	200	SOD-882	datasheet
MM8D 5V1	4	4.85	-	5.36	5	200	SOD-882	datasheet
MM8D 5V6	5*	5.32	-	5.88	5	200	SOD-882	datasheet
MM8D 6V2	6	5.89	-	6.51	5	200	SOD-882	datasheet
MM8D 6V8	A*	6.46	-	7.14	5	200	SOD-882	datasheet
MM8D 7V5	D*	7.13	-	7.88	5	200	SOD-882	datasheet
MM8D 8V2	E*	7.79	-	8.61	5	200	SOD-882	datasheet
MM8D 9V1	F*	8.65	-	9.56	5	200	SOD-882	datasheet
MM8D 10V	J*	9.5	-	10.5	5	200	SOD-882	datasheet
MM8D 11V	K*	10.45	-	11.55	5	200	SOD-882	datasheet
MM8D	L*	11.	-	12.	5	200	SOD-8	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
12V		4		6			82	eet
MM8D13V	P*	12.35	-	13.65	5	200	SOD-882	datasheet
MM8D15V	Q*	14.25	-	15.75	5	200	SOD-882	datasheet
MM8D16V	R*	15.2	-	16.8	5	200	SOD-882	datasheet
MM8D18V	T*	17.1	-	18.9	5	200	SOD-882	datasheet
MM8D20V	V*	19	-	21	5	200	SOD-882	datasheet
MM8D22V	Y*	20.9	-	23.1	5	200	SOD-882	datasheet
MM8D24V	S	22.8	-	25.2	5	200	SOD-882	datasheet
MM5Z2V4	00	2.2	2.4	2.6	5	150	SOD-523	datasheet
MM5Z2V7	01	2.5	2.7	2.9	5	150	SOD-523	datasheet
MM5Z3V0	02	2.8	3	3.2	5	150	SOD-523	datasheet
MM5Z3V3	05	3.1	3.3	3.5	5	150	SOD-523	datasheet
MM5Z3V6	06	3.4	3.6	3.8	5	150	SOD-523	datasheet
MM5Z3V9	07	3.7	3.9	4.1	5	150	SOD-523	datasheet
MM5Z4V3	08	4	4.3	4.6	5	150	SOD-523	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
MM5Z4V7	09	4.4	4.7	5	5	150	SOD-523	datasheet
MM5Z5V1	0A	4.8	5.1	5.4	5	150	SOD-523	datasheet
MM5Z5V6	0C	5.2	5.6	6	5	150	SOD-523	datasheet
MM5Z6V2	0E	5.8	6.2	6.6	5	150	SOD-523	datasheet
MM5Z6V8	0F	6.4	6.8	7.2	5	150	SOD-523	datasheet
MM5Z7V5	0G	7	7.5	7.9	5	150	SOD-523	datasheet
MM5Z8V2	0H	7.7	8.2	8.7	5	150	SOD-523	datasheet
MM5Z9V1	0K	8.5	9.1	9.6	5	150	SOD-523	datasheet
MM5Z10V	0L	9.4	10	10.6	5	150	SOD-523	datasheet
MM5Z11V	0M	10.4	11	11.6	5	150	SOD-523	datasheet
MM5Z12V	0N	11.4	12	12.7	5	150	SOD-523	datasheet
MM5Z13V	0P	12.4	13.25	14.1	5	150	SOD-523	datasheet
MM5Z15V	0T	14.3	15	15.8	5	150	SOD-523	datasheet
MM5Z16V	0U	15.3	16.2	17.1	2	150	SOD-523	datasheet
MM5Z	0W	16.	18	19.	2	150	SOD-5	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
18V		8		1			23	eet
MM5Z 20V	0Z	18.8	20	21.2	2	150	SOD-523	datasheet
MM5Z 22V	10	20.8	22	23.3	2	150	SOD-523	datasheet
MM5Z 24V	11	22.8	24.2	25.6	2	150	SOD-523	datasheet
MM5Z 27V	12	25.1	27	28.9	2	150	SOD-523	datasheet
MM5Z 30V	14	28	30	32	2	150	SOD-523	datasheet
MM5Z 33V	18	31	33	35	2	150	SOD-523	datasheet
MM5Z 36V	19	34	36	38	2	150	SOD-523	datasheet
MM5Z 39V	20	37	39	41	2	150	SOD-523	datasheet
MM5Z 43V	21	40	43	46	1	150	SOD-523	datasheet
MM5Z 47V	1A	44	47	50	1	150	SOD-523	datasheet
MM5Z 51V	1C	48	51	54	1	150	SOD-523	datasheet
MM5Z 56V	1D	52	56	60	1	150	SOD-523	datasheet
MM5Z 62V	1E	58	62	66	1	150	SOD-523	datasheet
MM5Z 68V	1F	64	68	72	1	150	SOD-523	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
MM5Z75V	1G	70	75	79	1	150	SOD-523	datasheet
EDZ2.4B	22	2.43	-	2.63	5	150	SOD-523	datasheet
EDZ2.7B	32	2.69	-	2.91	5	150	SOD-523	datasheet
EDZ3.0B	42	3.01	-	3.22	5	150	SOD-523	datasheet
EDZ3.3B	52	3.32	-	3.53	5	150	SOD-523	datasheet
EDZ3.6B	62	3.6	-	3.85	5	150	SOD-523	datasheet
EDZ3.9B	72	3.89	-	4.16	5	150	SOD-523	datasheet
EDZ4.3B	82	4.17	-	4.43	5	150	SOD-523	datasheet
EDZ4.7B	92	4.55	-	4.75	5	150	SOD-523	datasheet
EDZ5.1B	A2	4.98	-	5.2	5	150	SOD-523	datasheet
EDZ5.6B	C2	5.49	-	5.73	5	150	SOD-523	datasheet
EDZ6.2B	E2	6.06	-	6.33	5	150	SOD-523	datasheet
EDZ6.8B	F2	6.65	-	6.93	5	150	SOD-523	datasheet
EDZ7.5B	H2	7.28	-	7.6	5	150	SOD-523	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
EDZ8.2B	J2	8.02	-	8.36	5	150	SOD-523	datasheet
EDZ9.1B	L2	8.85	-	9.23	5	150	SOD-523	datasheet
EDZ10B	5	9.77	-	10.21	5	150	SOD-523	datasheet
EDZ11B	15	10.76	-	11.22	5	150	SOD-523	datasheet
EDZ12B	25	11.74	-	12.24	5	150	SOD-523	datasheet
EDZ13B	35	12.91	-	13.49	5	150	SOD-523	datasheet
EDZ15B	45	14.34	-	14.98	5	150	SOD-523	datasheet
EDZ16B	55	15.85	-	16.51	5	150	SOD-523	datasheet
EDZ18B	65	17.56	-	18.35	5	150	SOD-523	datasheet
EDZ20B	75	19.52	-	20.39	5	150	SOD-523	datasheet
EDZ22B	85	21.54	-	22.47	5	150	SOD-523	datasheet
EDZ24B	95	23.72	-	24.78	5	150	SOD-523	datasheet
EDZ27B	A5	26.19	-	27.53	2	150	SOD-523	datasheet
EDZ30B	C5	29.19	-	30.69	2	150	SOD-523	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
EDZ33B	E5	32.15	-	33.79	2	150	SOD-523	datasheet
EDZ36B	F5	35.07	-	36.87	2	150	SOD-523	datasheet
MM3Z2V0	WY	1.91	2	2.09	5	200	SOD-323	datasheet
MM3Z2V4	00	2.2	2.4	2.6	5	200	SOD-323	datasheet
MM3Z2V7	01	2.5	2.7	2.9	5	200	SOD-323	datasheet
MM3Z3V0	02	2.8	3	3.2	5	200	SOD-323	datasheet
MM3Z3V3	05	3.1	3.3	3.5	5	200	SOD-323	datasheet
MM3Z3V6	06	3.4	3.6	3.8	5	200	SOD-323	datasheet
MM3Z3V9	07	3.7	3.9	4.1	5	200	SOD-323	datasheet
MM3Z4V3	08	4	4.3	4.6	5	200	SOD-323	datasheet
MM3Z4V7	09	4.4	4.7	5	5	200	SOD-323	datasheet
MM3Z5V1	0A	4.8	5.1	5.4	5	200	SOD-323	datasheet
MM3Z5V6	0C	5.2	5.6	6	5	200	SOD-323	datasheet
MM3Z6V2	0E	5.8	6.2	6.6	5	200	SOD-323	datasheet
MM3Z6	0F	6.4	6.8	7.2	5	200	SOD-	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
V8							323	eet
MM3Z7V5	0G	7	7.5	7.9	5	200	SOD-323	datasheet
MM3Z8V2	0H	7.7	8.2	8.7	5	200	SOD-323	datasheet
MM3Z9V1	0K	8.5	9.1	9.6	5	200	SOD-323	datasheet
MM3Z10V	0L	9.4	10	10.6	5	200	SOD-323	datasheet
MM3Z11V	0M	10.4	11	11.6	5	200	SOD-323	datasheet
MM3Z12V	0N	11.4	12	12.7	5	200	SOD-323	datasheet
MM3Z13V	0P	12.4	13.25	14.1	5	200	SOD-323	datasheet
MM3Z15V	0T	14.3	15	15.8	5	200	SOD-323	datasheet
MM3Z16V	0U	15.3	16.2	17.1	5	200	SOD-323	datasheet
MM3Z18V	0W	16.8	18	19.1	5	200	SOD-323	datasheet
MM3Z20V	0Z	18.8	20	21.2	5	200	SOD-323	datasheet
MM3Z22V	10	20.8	22	23.3	5	200	SOD-323	datasheet
MM3Z24V	11	22.8	24.2	25.6	5	200	SOD-323	datasheet
MM3Z27V	12	25.1	27	28.9	2	200	SOD-323	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
MM3Z30V	14	28	30	32	2	200	SOD-323	datasheet
MM3Z33V	18	31	33	35	2	200	SOD-323	datasheet
MM3Z36V	19	34	36	38	2	200	SOD-323	datasheet
MM3Z39V	20	37	39	41	2	200	SOD-323	datasheet
MM3Z43V	21	40	43	46	2	200	SOD-323	datasheet
MM3Z47V	1A	44	47	50	2	200	SOD-323	datasheet
MM3Z51V	1C	48	51	54	2	200	SOD-323	datasheet
MM3Z56V	1D	52	56	60	2	200	SOD-323	datasheet
MM3Z62V	1E	58	62	66	2	200	SOD-323	datasheet
MM3Z68V	1F	64	68	72	2	200	SOD-323	datasheet
MM3Z75V	1G	70	75	79	2	200	SOD-323	datasheet
UDZS2.0B	2	2.02	-	2.2	5	200	SOD-323	datasheet
UDZS2.2B	12	2.22	-	2.41	5	200	SOD-323	datasheet
UDZS2.4B	22	2.43	-	2.63	5	200	SOD-323	datasheet
UDZS2.5B	32	2.6	-	2.9	5	200	SOD-323	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
7B		9		1			323	eet
UDZS3.0B	42	3.01	-	3.22	5	200	SOD-323	datasheet
UDZS3.3B	52	3.32	-	3.53	5	200	SOD-323	datasheet
UDZS3.6B	62	3.6	-	3.85	5	200	SOD-323	datasheet
UDZS3.9B	72	3.89	-	4.16	5	200	SOD-323	datasheet
UDZS4.3B	82	4.17	-	4.43	5	200	SOD-323	datasheet
UDZS4.7B	92	4.55	-	4.75	5	200	SOD-323	datasheet
UDZS5.1B	A2	4.98	-	5.2	5	200	SOD-323	datasheet
UDZS5.6B	C2	5.49	-	5.73	5	200	SOD-323	datasheet
UDZS6.2B	E2	6.06	-	6.33	5	200	SOD-323	datasheet
UDZS6.8B	F2	6.65	-	6.93	5	200	SOD-323	datasheet
UDZS7.5B	H2	7.28	-	7.6	5	200	SOD-323	datasheet
UDZS8.2B	J2	8.02	-	8.36	5	200	SOD-323	datasheet
UDZS9.1B	L2	8.85	-	9.23	5	200	SOD-323	datasheet
UDZS10B	5	9.77	-	10.21	5	200	SOD-323	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
UDZS11B	15	10.76	-	11.22	5	200	SOD-323	datasheet
UDZS12B	25	11.74	-	12.24	5	200	SOD-323	datasheet
UDZS13B	35	12.91	-	13.49	5	200	SOD-323	datasheet
UDZS15B	45	14.34	-	14.98	5	200	SOD-323	datasheet
UDZS16B	55	15.85	-	16.51	5	200	SOD-323	datasheet
UDZS18B	65	17.56	-	18.35	5	200	SOD-323	datasheet
UDZS20B	75	19.52	-	20.39	5	200	SOD-323	datasheet
UDZS22B	85	21.54	-	22.47	5	200	SOD-323	datasheet
UDZS24B	95	23.72	-	24.78	5	200	SOD-323	datasheet
UDZS27B	A5	26.19	-	27.53	5	200	SOD-323	datasheet
UDZS30B	C5	29.19	-	30.69	5	200	SOD-323	datasheet
UDZS33B	E5	32.15	-	33.79	5	200	SOD-323	datasheet
UDZS36B	F5	35.07	-	36.87	5	200	SOD-323	datasheet
BZT52B2V0	02	2.02	-	2.2	5	500	SOD-123	datasheet
BZT52B	12	2.2	-	2.4	5	500	SOD-	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
2V2		2		1			123	eet
BZT52B 2V4	22	2.43	-	2.63	5	500	SOD-123	datasheet
BZT52B 2V7	32	2.69	-	2.91	5	500	SOD-123	datasheet
BZT52B 3V0	42	3.01	-	3.22	5	500	SOD-123	datasheet
BZT52B 3V3	52	3.32	-	3.53	5	500	SOD-123	datasheet
BZT52B 3V6	62	3.6	-	3.85	5	500	SOD-123	datasheet
BZT52B 3V9	72	3.89	-	4.16	5	500	SOD-123	datasheet
BZT52B 4V3	82	4.17	-	4.43	5	500	SOD-123	datasheet
BZT52B 4V7	92	4.55	-	4.75	5	500	SOD-123	datasheet
BZT52B 5V1	A2	4.98	-	5.2	5	500	SOD-123	datasheet
BZT52B 5V6	C2	5.49	-	5.73	5	500	SOD-123	datasheet
BZT52B 6V2	E2	6.06	-	6.33	5	500	SOD-123	datasheet
BZT52B 6V8	F2	6.65	-	6.93	5	500	SOD-123	datasheet
BZT52B 7V5	H2	7.28	-	7.6	5	500	SOD-123	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
BZT52B8V2	J2	8.02	-	8.36	5	500	SOD-123	datasheet
BZT52B9V1	L2	8.85	-	9.23	5	500	SOD-123	datasheet
BZT52B10	05	9.77	-	10.21	5	500	SOD-123	datasheet
BZT52B11	15	10.76	-	11.22	5	500	SOD-123	datasheet
BZT52B12	25	11.74	-	12.24	5	500	SOD-123	datasheet
BZT52B13	35	12.91	-	13.49	5	500	SOD-123	datasheet
BZT52B15	45	14.34	-	14.98	5	500	SOD-123	datasheet
BZT52B16	55	15.85	-	16.51	5	500	SOD-123	datasheet
BZT52B18	65	17.56	-	18.35	5	500	SOD-123	datasheet
BZT52B20	75	19.52	-	20.39	5	500	SOD-123	datasheet
BZT52B22	85	21.54	-	22.47	5	500	SOD-123	datasheet
BZT52B24	95	23.72	-	24.78	5	500	SOD-123	datasheet
BZT52B27	A5	26.19	-	27.53	5	500	SOD-123	datasheet
BZT52B30	C5	29.19	-	30.69	5	500	SOD-123	datasheet
BZT52B3	E5	32.	-	33.	5	500	SOD-	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
3		15		79			123	eet
BZT52B36	F5	35.07	-	36.87	5	500	SOD-123	datasheet
BZT52C2V4	WX	2.2	2.4	2.6	5	500	SOD-123	datasheet
BZT52C2V7	W1	2.5	2.7	2.9	5	500	SOD-123	datasheet
BZT52C3V0	W2	2.8	3	3.2	5	500	SOD-123	datasheet
BZT52C3V3	W3	3.1	3.3	3.5	5	500	SOD-123	datasheet
BZT52C3V6	W4	3.4	3.6	3.8	5	500	SOD-123	datasheet
BZT52C3V9	W5	3.7	3.9	4.1	5	500	SOD-123	datasheet
BZT52C4V3	W6	4	4.3	4.6	5	500	SOD-123	datasheet
BZT52C4V7	W7	4.4	4.7	5	5	500	SOD-123	datasheet
BZT52C5V1	W8	4.8	5.1	5.4	5	500	SOD-123	datasheet
BZT52C5V6	W9	5.2	5.6	6	5	500	SOD-123	datasheet
BZT52C6V2	WA	5.8	6.2	6.6	5	500	SOD-123	datasheet
BZT52C6V8	WB	6.4	6.8	7.2	5	500	SOD-123	datasheet
BZT52C7V5	WC	7	7.5	7.9	5	500	SOD-123	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
BZT52C8V2	WD	7.7	8.2	8.7	5	500	SOD-123	datasheet
BZT52C9V1	WE	8.5	9.1	9.6	5	500	SOD-123	datasheet
BZT52C10	WF	9.4	10	10.6	5	500	SOD-123	datasheet
BZT52C11	WG	10.4	11	11.6	5	500	SOD-123	datasheet
BZT52C12	WH	11.4	12	12.7	5	500	SOD-123	datasheet
BZT52C13	WI	12.4	13	14.1	5	500	SOD-123	datasheet
BZT52C15	WJ	13.8	15	15.8	5	500	SOD-123	datasheet
BZT52C16	WK	15.3	16	17.1	5	500	SOD-123	datasheet
BZT52C18	WL	16.8	18	19.1	5	500	SOD-123	datasheet
BZT52C20	WM	18.8	20	21.2	5	500	SOD-123	datasheet
BZT52C22	WN	20.8	22	23.3	5	500	SOD-123	datasheet
BZT52C24	WO	22.8	24	25.6	5	500	SOD-123	datasheet
BZT52C27	WP	25.1	27	28.9	2	500	SOD-123	datasheet
BZT52C30	WQ	28	30	32	2	500	SOD-123	datasheet
BZT52C3	WR	31	33	35	2	500	SOD-	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
3							123	eet
BZT52C36	WS	34	36	38	2	500	SOD-123	datasheet
BZT52C39	WT	37	39	41	2	500	SOD-123	datasheet
BZT52C43	WU	40	43	46	2	500	SOD-123	datasheet
BZT52C47	WV	44	47	50	2	500	SOD-123	datasheet
BZT52C51	WW	48	51	54	2	500	SOD-123	datasheet
MMSZ5221B	C1	2.28	2.4	2.52	20	500	SOD-123	datasheet
MMSZ5222B	C2	2.38	2.5	2.63	20	500	SOD-123	datasheet
MMSZ5223B	C3	2.57	2.7	2.84	20	500	SOD-123	datasheet
MMSZ5224B	C4	2.66	2.8	2.94	20	500	SOD-123	datasheet
MMSZ5225B	C5	2.85	3	3.15	20	500	SOD-123	datasheet
MMSZ5226B	D1	3.14	3.3	3.47	20	500	SOD-123	datasheet
MMSZ5227B	D2	3.42	3.6	3.78	20	500	SOD-123	datasheet
MMSZ5228B	D3	3.71	3.9	4.1	20	500	SOD-123	datasheet
MMSZ5229B	D4	4.09	4.3	4.52	20	500	SOD-123	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
MMSZ5230B	D5	4.47	4.7	4.94	20	500	SOD-123	datasheet
MMSZ5231B	E1	4.85	5.1	5.36	20	500	SOD-123	datasheet
MMSZ5232B	E2	5.32	5.6	5.88	20	500	SOD-123	datasheet
MMSZ5233B	E3	5.7	6	6.3	20	500	SOD-123	datasheet
MMSZ5234B	E4	5.89	6.2	6.51	20	500	SOD-123	datasheet
MMSZ5235B	E5	6.46	6.8	7.14	20	500	SOD-123	datasheet
MMSZ5236B	F1	7.13	7.5	7.88	20	500	SOD-123	datasheet
MMSZ5237B	F2	7.79	8.2	8.61	20	500	SOD-123	datasheet
MMSZ5238B	F3	8.27	8.7	9.14	20	500	SOD-123	datasheet
MMSZ5239B	F4	8.65	9.1	9.56	20	500	SOD-123	datasheet
MMSZ5240B	F5	9.5	10	10.5	20	500	SOD-123	datasheet
MMSZ5241B	H1	10.45	11	11.55	20	500	SOD-123	datasheet
MMSZ5242B	H2	11.4	12	12.6	20	500	SOD-123	datasheet
MMSZ5243B	H3	12.35	13	13.65	9.5	500	SOD-123	datasheet
MMSZ52	H4	13.	14	14.	9	500	SOD-	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
44B		3		7			123	eet
MMSZ5245B	H5	14.25	15	15.75	8.5	500	SOD-123	datasheet
MMSZ5246B	J1	15.2	16	16.8	7.8	500	SOD-123	datasheet
MMSZ5247B	J2	16.15	17	17.85	7.4	500	SOD-123	datasheet
MMSZ5248B	J3	17.1	18	18.9	7	500	SOD-123	datasheet
MMSZ5250B	J5	19	20	21	6.2	500	SOD-123	datasheet
MMSZ5251B	K1	20.9	22	23.1	5.6	500	SOD-123	datasheet
MMSZ5252B	K2	22.8	24	25.2	5.2	500	SOD-123	datasheet
MMSZ5253B	K3	23.75	25	26.25	5	500	SOD-123	datasheet
MMSZ5254B	K4	25.65	27	28.35	4.6	500	SOD-123	datasheet
MMSZ5255B	K5	26.6	28	29.4	4.5	500	SOD-123	datasheet
MMSZ5256B	M1	28.5	30	31.5	4.2	500	SOD-123	datasheet
MMSZ5257B	M2	31.35	33	34.65	3.8	500	SOD-123	datasheet
MMSZ5258B	M3	34.2	36	37.8	3.4	500	SOD-123	datasheet
MMSZ5259B	M4	37.05	39	40.95	3.2	500	SOD-123	datasheet

Device	Device Marking	VZ (V) Min	VZ (V) Nom	VZ (V) Max	@ IZT (mA)	PD(mW)	Package	PDF Datasheet
MMSZ5260B	M5	40.85	43	45.15	3	500	SOD-123	datasheet
MMSZ5261B	N1	44.65	47	49.35	2.7	500	SOD-123	datasheet
MMSZ5262B	N2	48.45	51	53.55	2.5	500	SOD-123	datasheet
MMSZ5263B	N3	53.2	56	58.8	2.2	500	SOD-123	datasheet
MMSZ5264B	N4	57	60	63	2.1	500	SOD-123	datasheet
MMSZ5265B	N5	58.9	62	65.1	2	500	SOD-123	datasheet
MMSZ5266B	P1	64.6	68	71.4	1.8	500	SOD-123	datasheet
MMSZ5267B	P2	71.25	75	78.75	1.7	500	SOD-123	datasheet
MMSZ5268B	P3	77.9	82	86.1	1.5	500	SOD-123	datasheet
MMSZ5269B	P4	82.65	87	91.35	1.4	500	SOD-123	datasheet
MMSZ5270B	P5	86.45	91	95.55	1.4	500	SOD-123	datasheet
MMSZ5272B	R2	104.5	110	115.5	1.1	500	SOD-123	datasheet